

### WARNING: Failure to read and carefully follow these instructions may jeopardize subscriber security!

**INTRODUCTION:** The NNT3CH is a Long Range Alarm Radio Transmitter for use on the NearNet Alarm Radio Network (see coverage map below). NearNet processors forward these radio signals to the Central Station via standard communicator techniques. Several times per day the unit automatically communicates with the network, and the network will generate and report a Communications Failure signal in the event that the network does not receive any of these supervisory test signals over a calendar day.

### INSTALLATION GUIDELINES


(Complete Installation Instructions Begin on Next Page)

- Mounting locations can **ONLY** be selected based on RF performance, therefore, it is **HIGHLY** recommended that the installer follow the **SELECTING A MOUNTING LOCATION** section below **BEFORE** any wires are run to the alarm control panel.
- Generally, high locations are best. **DO NOT** mount radio in basement or below grade as unpredictable performance may result.
- Whenever possible, keep the transmitter in a climate controlled environment. Attics may reach extremely high temperatures in summer months. Unheated garages may reach extremely cold temperatures in winter months.
- Avoid locations within 3 feet of large metal objects (air conditioners, metal garage doors, etc.), AC power lines, and fluorescent light fixtures.
- A fair amount of care may be required to mount the unit so as to achieve an optimal RF path. While NearNet does not place restrictions on installers to reach a certain number of receive sites (see map below), it is always best to reach as many sites as possible to ensure reliable performance now and in the future.
- Unlike smoke detectors, motion detectors, etc., these transmitters draw a substantial amount of current (approximately 1 Amp during transmit) and require a "clean" 12VDC power source, free from any AC ripple or "noise". Therefore, follow the instructions for **POWER** contained herein **EXACTLY!** Power the unit from a battery as shown. **DO NOT** power from the alarm control panel "AUX" power output or directly from a power supply. **DO NOT** vary from the Wiring Size Chart. Failure to properly power the unit may cause unpredictable performance over time.

### SELECTING A MOUNTING LOCATION

- Install the antenna as shown in Section 1 on the reverse side.
- Temporarily connect power to the transmitter from a fully charged 12V (4AH minimum) battery. **DO NOT** mount the transmitter at this time. Temporarily position the unit in the desired mounting location.
- Follow the **MANUAL TEST** (Section 3) instruction on the reverse side. Move the unit as required for reliable results. It is best to be received at more than one receive site, however it is acceptable to be received at only one receive site provided that 90% (9 out of 10) of signals sent are received.


## NORTH EAST ALARM RADIO NETWORK COVERAGE AREA



# 1 ANTENNA INSTALLATION

- Gently push antenna rod straight down into antenna jack until it stops.
- Slide grommet down antenna rod and snap into place in hole on top of transmitter case.


TRANSMITTER - TOP VIEW



**NEVER POWER UNIT WITHOUT ANTENNA INSTALLED!!!  
DAMAGE WILL RESULT!!!**

# 2 POWER

- Connect 12VDC from battery as shown.



**WIRE AS SHOWN ABOVE ONLY!  
DO NOT POWER FROM "AUX" OUTPUT OR  
DIRECTLY FROM POWER SUPPLY!**

### WIRE SIZE CHART

UP to 10 FEET	10 to 50 FEET	50 to 100 FEET
22 Gauge	18 Gauge	14 Gauge

\* If a stand-alone power supply is used, the negative (-) terminal must be connected to the negative (-) terminal of the control panel. Failure to provide this common negative will prevent the input channels from being triggered.

# 3 MANUAL TEST


- Send manual test (Code Ø) signals by pressing TEST BUTTON (S2). The LED will light for approximately 1 second each time a signal is transmitted. Call the NearNet Automated Signal Verification System at (631) 736-7123 (select option 5) to verify which sites are receiving the signals.



## 4 WIRE INPUT CHANNELS

Follow **VOLTAGE TRIGGER** methods for ADEMCO and most other Alarm Control Panels with voltage trigger outputs

Follow **GROUND TRIGGER** methods for DSC, NAPCO and most other Alarm Control Panels with electronic pull-to-ground trigger outputs



### VOLTAGE TRIGGER:

**DO NOT** CUT RESISTOR R3

CONNECT CHANNEL 3 TO CONTROL PANEL "BELL +" or OTHER VOLTAGE (+4.5 to 14.5VDC) TRIGGER – UNIT WILL SEND CODE 3

### GROUND TRIGGER:

WITH POWER REMOVED, **CUT** RESISTOR R3

CONNECT CHANNEL 3 TO CONTROL PANEL "BELL -" (DSC) or "E-LUG" (NAPCO) OR OTHER PULL-TO-GROUND TRIGGER – UNIT WILL SEND CODE 3

### VOLTAGE TRIGGER:

**DO NOT** CUT RESISTOR R2

CONNECT CHANNEL 2 TO CONTROL PANEL "BELL +" or OTHER VOLTAGE (+4.5 to 14.5VDC) TRIGGER – UNIT WILL SEND CODE 2

### GROUND TRIGGER:

WITH POWER REMOVED, **CUT** RESISTOR R2

CONNECT CHANNEL 2 TO CONTROL PANEL "BELL -" (DSC) or "E-LUG" (NAPCO) OR OTHER PULL-TO-GROUND TRIGGER – UNIT WILL SEND CODE 2

### VOLTAGE TRIGGER:

**DO NOT** CUT RESISTOR R1

CONNECT CHANNEL 1 TO CONTROL PANEL "BELL +" or OTHER VOLTAGE (+4.5 to 14.5VDC) TRIGGER – UNIT WILL SEND CODE 1

### GROUND TRIGGER:

WITH POWER REMOVED, **CUT** RESISTOR R1

CONNECT CHANNEL 1 TO CONTROL PANEL "BELL -" (DSC) or "E-LUG" (NAPCO) OR OTHER PULL-TO-GROUND TRIGGER – UNIT WILL SEND CODE 1

All input channels send 5 signals when triggered, with a random delay between signals. LED will light for approximately 1 second each time a signal is transmitted.

## 5 VERIFY INSTALLATION

- Confirm each input channel is triggered by control panel output by calling the NearNet Automated Signal Verification System at (631) 696-7496, and verify which sites are receiving the signals. Note: The Central Station will not receive signals until the Transmitter Data Form is completed and faxed (see Step 6, below).

## 6 COMPLETE & SUBMIT PAPERWORK

- Complete the form on the back of this sheet and fax it to the number shown on the top of the form.